



eos Made in Germany

# DE KONINGH



## **Types**

### One concept, two sizes

The EOS series combines all functions of a solid label printer with highest operating comfort.





# *eo*52, the compact one for label roll diameters up to 152 mm

Label printer		EO	<b>S</b> 2
Printable resolution	dpi	203	300
Print speed	up to mm/s	150	150
Print width	up to mm	108	105.7
Label roll diameter	up to mm	152	152
Power supply		100 - 240 VA	C, 50/60 Hz

### eos5 for large label rolls

with diameters up to 203 mm

Label printer		EO	S 5
Printable resolution	dpi	203	300
Print speed	up to mm/s	150	150
Print width	up to mm	108	105.7
Label roll diameter	up to mm	203	203
Power supply		100 - 240 VA	C, 50/60 Hz

## Mobile printing

in production, warehousing or agriculture, wherever labels are required and access to electricity is missing. 24 V input voltage enable the printer to be power supplied by any powerful battery. For technical battery data see accessories





#### **eo**S2 mobile

for label roll diameters up to 152 mm

Label printer		EOS 2 mobile
Printable resolution	dpi	300*
Print speed	up to mm/s	150
Print width	up to mm	105.7
Label roll diameter	up to mm	152
Power supply		16.5 - 25 VDC

#### **eo**S5 mobile

for label roll diameters up to 203 mm

Label printer		EOS 5 mobile
Printable resolution	dpi	300*
Print speed	up to mm/s	150
Print width	up to mm	105.7
Label roll diameter	up to mm	203
Power supply		16.5 - 25 VDC

## DE KONING

## **Details**



To achieve accurate imprint with slim materials and ribbons, slim print rollers are needed. These prevent from print roller wear, print head contamination and errors during material feed.

#### Roll holder

The label roll is inserted and automatically centered when closing.

#### Ribbon holder

The stop can be adjusted according to the ribbon width.

#### 9 Print head 203 / 300 dpi

In case of cleaning or wear, the print head can be replaced easily by hand without tools.

#### 4 Label sensor - gap or reflective

The sensor position can be adjusted via a spindle using the red rotary knob. The chosen position is indicated by a LED.

#### Print roller DR4

In case of cleaning or wear, the print roller can be replaced without tools.

#### 6 Material guide

Using the rotary knob, the guides can be adjusted to the material width

#### Tear-off plate

made of thin sheet steel: jagged, so labels are cleanly separated

## Operation panel

Intuitive and easy operation with self-explanatory symbols to configure the device setups

1 LED signal: Power ON

Status bar: Data reception, Record data stream, Ribbon pre-warning,

SD memory card / USB memory stick, Bluetooth,

WLAN, Ethernet, USB slave, Time

3 Printer status: Ready, Pause, Number of printed labels per print job,

Label in peel-off position, Awaiting external start signal

USB slot for the Service Key or a memory stick,

to load data in the IFFS storage

Operation:

Cutter / perforation cutter: cutting Tear-off mode: print label

Jump to menu

Stop and delete all print jobs

Reprint last label

Label feed

Interrupt and continue print job



## Interfaces on the back of the device



- for a SD memory card
- 2 x USB host to connect a Service Key, USB memory stick, keyboard, barcode scanner, USB Bluetooth adapter, USB WLAN stick
- USB 2.0 Hi-speed Device to connect a PC
- 4 Ethernet 10/100 BASE-T
- 5 RS232C 1,200 to 230,400 baud/8 bit

## Technical data

		1.1	1.	2	1.3	1.4
Label printer Type		EOS 2	EO	S 5	EOS 2 mobile	EOS 5 mobile
Material feed				cente	red	
Printing	Thermal transfer	•			•	•
method	Thermal direct	•			•	•
Printable resolution			500 203	300	300	300
Print speed Print width	up to mm/s up to mm		.50 150 05.7 108	150 105.7	150 105.7	150 105.7
Start of printing	Distance to locating edge mm	100 10	J3.1 100	cente		103.1
Material <sup>1)</sup>	Distance to tocating eage			cente	reu	
Paper, cardboard,	PI, PVC, PU, acrylate, Tyvec	•		)	•	•
Shrink tubes	ready-for-use	•			=	-
	continuous, pressed	•			-	-
Textile tapes		•			•	•
Packing	on rolls, reels				•	•
	Fanfold				-	-
	Roll diameter up to mm	152	20		152	203
	Core diameter mm			38.1		
ahala	Winding			outside o		
_abels	Width single-lane mm			10 -		
	multi-lane mm			5 - 3	116	
	Height excl. label backfeed from mm			5		
	incl. label backfeed from mm			12		
inor metarial	Thickness mm			0.05		
iner material	Width mm			25 - 1		
Continuous material	Thickness mm			0.05 - 5 - 1		
continuous material						
	Thickness mm Weight (cardboard) up to g/m²			0.05		
Shrink tubes	Width ready-for-use up to mm			12		
omink tubes	continuous, pressed mm			5 - 8		
	Thickness up to mm			1.		
Ribbon <sup>2)</sup>	Ink side			outside o		
KIDDOII ·	Roll diameter up to mm			72		
	Core diameter mm	25.4				
	Variable length up to m			36		
	Width mm			25 -		
Printer sizes and we						
Width x Height x Dep		253 x 189 x 32	22 264 x 24	5 x 412	253 x 189 x 322	264 x 245 x 412
Veight	kg	4	5		4	5
	ting the position					
Label sensor indica		labels or punch	marks and end of ma	terial, print m	arks on transparant mate	rials
	for		of material, print marl	ks on non-trar	·	
Gap sensor	reflex from below or top for	labels and end o				
Gap sensor Reflective sensor Distance of sensor		labels and end o		0 - :		
Gap sensor Reflective sensor Distance of sensor Material passage	reflex from below or top for	labels and end o		0 - :		
Gap sensor Reflective sensor Distance of sensor Material passage Electronics	reflex from below or top for from centre to locating edge centered mm up to mm	labels and end o		4		
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc	reflex from below or top for from centre to locating edge centered mm up to mm	labels and end o		80	0	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM)	reflex from below or top for from centre to locating edge centered mm up to mm	labels and end o		80 25	0	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS)	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB	labels and end o		80 25 50	0	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB	labels and end o		4 80 25 50 51	0 6 )	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock	labels and end o		80 25 50 51	0 6 )	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB	labels and end o		4 80 25 50 51	0 6 )	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and Data memory when paterfaces	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)	labels and end o		4 80 25 50 51	0 6 1 2 2	
Sap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and Data memory when p Interfaces RS232C 1,200 to 230,	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)	labels and end o		80 25 50 51	0 6 1 2 2	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and Data memory when p nterfaces RS232C 1,200 to 230,	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)		Deviative DUGO	80 25 50 51	0 6	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and Data memory when paterfaces RS232C 1,200 to 230, USB 2.0 Hi-speed dev	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC	LPD, IPv4, Rawl	P printing, DHCP, HTT conf, SOAP web servi	80 25 55 51	0 6 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Blot to connect a SD Battery for time and Data memory when p Interfaces RS232C 1,200 to 230, USB 2.0 Hi-speed dev Ethernet 10/100 BAS	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T	LPD, IPv4, Rawli TIME, NTP, Zero		80 25 55 51	0 6 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9 9	
Battery for time and Data memory when posterfaces RS232C 1,200 to 230, USB 2.0 Hi-speed development 10/100 BAS 1 x USB host on the o	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  operation panel for	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or U Service Key, USI	conf, SOAP web servi JSB memory stick B memory stick, keyb	80 25 50 51 P/HTTPS, FTP ce, VNC oard, barcode	0 6 0 2 2 /FTPS, SMTP, SNMP,	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and Data memory when paterfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS L x USB host on the b	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  peration panel for back of the device for	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or U Service Key, USI	conf, SOAP web servi JSB memory stick	80 25 50 51 P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Sap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Blot to connect a SD Battery for time and Data memory when paterfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS  x USB host on the b DSB WLAN stick 2.4 6	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  MB  Mememory card (SDHC, SDXC) up to GB  date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  peration panel for back of the device for GHz 802.11b/g/n	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or U Service Key, USI	conf, SOAP web servi JSB memory stick B memory stick, keyb	80 25 50 51 P/HTTPS, FTP ce, VNC oard, barcode	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Gap sensor Reflective sensor Distance of sensor Aaterial passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Botto to connect a SD Battery for time and Data memory when p Interfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS  Ex USB host on the output USB WLAN stick 2.4 cu USB WLAN stick 2.4 cu USB WLAN stick 2.4 cu	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  MB  MB  MB  MB  MB  MB  MB  M	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or U Service Key, USI	conf, SOAP web servi JSB memory stick B memory stick, keyb	80 25 50 51 P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Gap sensor Reflective sensor Distance of sensor Asterial passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Blot to connect a SD Battery for time and Data memory when p Interfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS  Ex USB host on the or Ex USB host on the b USB WLAN stick 2.4 G Hotspot or Infrastruct	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  MB  MB  MB  MB  MB  MB  MB  M	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or U Service Key, USI	conf, SOAP web servi JSB memory stick B memory stick, keyb	80 25 50 51 P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 0 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Sap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Blot to connect a SD Battery for time and Data memory when p Interfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS  Ex USB host on the output DISB WLAN stick 2.4 G DISB WLAN stick 2.4 G DISB WLAN stick 2.4 G DISB Bluetooth adaptive DISB STAN STICK 2.4 G DISB Bluetooth adaptive DISB	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  k rate MHZ  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  operation panel for back of the device for GHz 802.11b/g/n  GHz 802.11b/g/n  GHz 802.11b/g/n + 5 GHz 802.11a/n/ac, cture Mode ter	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or U Service Key, USI	conf, SOAP web servi JSB memory stick B memory stick, keyb	80 25 50 51 P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 0 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Sap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Blot to connect a SD Battery for time and Data memory when p Interfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS Lx USB host on the b USB WLAN stick 2.4 G Hotspot or Infrastruc USB Bluetooth adapt Peripheral connectic	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  k rate MHZ  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  operation panel for back of the device for GHz 802.11b/g/n  GHz 802.11b/g/n  GHz 802.11b/g/n + 5 GHz 802.11a/n/ac, cture Mode ter	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or U Service Key, USI	conf, SOAP web servi JSB memory stick B memory stick, keyb	80 25 50 51 P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 0 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and Data memory when parteriaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS Lx USB host on the book as USB will be soon the book as USB WLAN stick 2.4 Goldston or Infrastruct USB Bluetooth adapt Peripheral connectic Deerating data	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  k rate MHZ  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  operation panel for back of the device for GHz 802.11b/g/n  GHz 802.11b/g/n  GHz 802.11b/g/n + 5 GHz 802.11a/n/ac, cture Mode ter	LPD, IPv4, Rawll TIME, NTP, Zero Service Key or U Service Key, USI USB Bluetooth a	conf, SOAP web servi JSB memory stick B memory stick, keyb adapter, USB WLAN st	P/HTTPS, FTP ce, VNC	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Blot to connect a SD Battery for time and Data memory when poster Interfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS Lx USB host on the book at SUSB will be soon the book at SUSB WLAN stick 2.4 Colors or Infrastruct USB Bluetooth adapt Peripheral connectic Decrating data Power supply	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  operation panel for back of the device for GHz 802.11b/g/n  GHz 802.11b/g/n  GHz 802.11b/g/n + 5 GHz 802.11a/n/ac, cture Mode ter on USB host, 24 VDC	LPD, IPv4, Rawll TIME, NTP, Zero Service Key or L Service Key, USI USB Bluetooth a	conf, SOAP web servi JSB memory stick B memory stick, keyb adapter, USB WLAN st	P/HTTPS, FTP ce, VNC	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	VDC
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Botto connect a SD Battery for time and Data memory when porterfaces RS232C 1,200 to 230, USB 2.0 Hi-speed dev Ethernet 10/100 BAS Lx USB host on the bottom of	reflex from below or top for from centre to locating edge centered mm up to mm  k rate MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  operation panel for back of the device for GHz 802.11b/g/n  GHz 802.11b/g/n  SHz 802.11b/g/n SHz 802.11a/n/ac, cture Mode ter	LPD, IPv4, Rawl TIME, NTP, Zero Service Key or U Service Key, USI USB Bluetooth a	oconf, SOAP web servi JSB memory stick B memory stick, keyb adapter, USB WLAN st WAO VAC, 50/60 Hz, PFC	80 25 51 51 P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	VDC
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Botto connect a SD Battery for time and Data memory when porterfaces RS232C 1,200 to 230, USB 2.0 Hi-speed dev Ethernet 10/100 BAS Lx USB host on the bottom of	reflex from below or top for from centre to locating edge centered mm up to mm  k rate  MHz  MB  MB  memory card (SDHC, SDXC) date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  peration panel for back of the device GHz 802.11b/g/n	LPD, IPv4, Rawl TIME, NTP, Zero Service Key or U Service Key, USI USB Bluetooth a 100 - 2 Standby 1,8 W / +5 - 40°C / 10 -	JSB memory stick B memory stick, keyb adapter, USB WLAN st WAC, 50/60 Hz, PFC typical 45 W 85 %, not condensing	80 25 51  P/HTTPS, FTP ce, VNC  oard, barcode ick, external c	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	VDC
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Slot to connect a SD Battery for time and Data memory when paterfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS Lx USB host on the b USB WLAN stick 2.4 6	reflex from below or top from centre to locating edge centered mm up to mm  k rate  MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  peration panel for back of the device GHz 802.11b/g/n	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or U Service Key, USI USB Bluetooth a 100 - 2 Standby 1,8 W/ +5 - 40°C / 10 - 0 - 60°C / 20 -	JSB memory stick B memory stick, keyb adapter, USB WLAN st WAC, 50/60 Hz, PFC typical 45 W 85 %, not condensing	80 25 51  P/HTTPS, FTP ce, VNC  oard, barcode ick, external c	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	VDC
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (RFS) Botto connect a SD Battery for time and Data memory when p Interfaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS L x USB host on the o DISB WLAN stick 2.4 G JSB WLAN stick 2.4 G JSB WLAN stick 2.4 G JSB Bluetooth adapt Peripheral connectic Diperating data Power supply Power consumption Temperature / humic	reflex from below or top for from centre to locating edge centered mm up to mm  k rate  MHz  MB  MB  memory card (SDHC, SDXC) date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  peration panel for back of the device GHz 802.11b/g/n	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or L Service Key, USI USB Bluetooth a 100 - 2 Standby 1,8 W/ +5 - 40°C / 10 - 0 - 60°C / 20 - -25 - 60°C / 20 -	JSB memory stick B memory stick, keyb adapter, USB WLAN st WAC, 50/60 Hz, PFC typical 45 W 85 %, not condensing 85 %, not condensing	4 80 25 50 51   P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 9 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Gap sensor Reflective sensor Distance of sensor Asterial passage Reflectronics Processor 32 bit clock Adain memory (RAM) Data memory (IFFS) Botto to connect a SD Battery for time and Data memory when pateriaces RS232C 1,200 to 230, JSB 2.0 Hi-speed dev Ethernet 10/100 BAS  Ex USB host on the object of the sensor of the sen	reflex from below or top from centre to locating edge centered mm up to mm  k rate  MHz  MB  MB  memory card (SDHC, SDXC) up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  peration panel for back of the device GHz 802.11b/g/n	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or L Service Key, USI USB Bluetooth a 100 - 2 Standby 1,8 W/ +5 - 40°C / 10 - 0 - 60°C / 20 - -25 - 60°C / 20 -	JSB memory stick B memory stick, keyb adapter, USB WLAN st WAC, 50/60 Hz, PFC typical 45 W 85 %, not condensing 85 %, not condensing	4 80 25 50 51   P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 0 2 2 /FTPS, SMTP, SNMP, scanner, peration panel	
Gap sensor Reflective sensor Distance of sensor Material passage Electronics Processor 32 bit cloc Main memory (RAM) Data memory (IFFS) Botto connect a SD Battery for time and Data memory when paterfaces RS232C 1,200 to 230, USB 2.0 Hi-speed dev Ethernet 10/100 BAS Ex USB host on the output DISB WLAN stick 2.4 G D DISB WLAN stick 2.4 G D D D D D D D D D D D D D D D D D D D	reflex from below or top from centre to locating edge centered mm up to mm  k rate  MHZ  MB  MB  memory card (SDHC, SDXC)  up to GB date, real-time clock power is switched off (e.g. serial numbering)  400 baud/8 bit vice to connect a PC  E-T  operation panel for back of the device GHz 802.11b/g/n	LPD, IPv4, Rawli TIME, NTP, Zero Service Key or L Service Key, USI USB Bluetooth a 100 - 2 Standby 1,8 W/ +5 - 40°C / 10 - 0 - 60°C / 20 - -25 - 60°C / 20 -	JSB memory stick B memory stick, keyb adapter, USB WLAN st WAC, 50/60 Hz, PFC typical 45 W 85 %, not condensing 85 %, not condensing	4 80 25 50 51   P/HTTPS, FTP ce, VNC oard, barcode ick, external c	0 6 9 2 /FTPS, SMTP, SNMP, scanner, peration panel	

<sup>&</sup>lt;sup>1)</sup> The material specifications are standard values. Applications with small labels, thin, slim, thick and stiff materials as well as strongly adherent labels have to be tested. <sup>2)</sup> The ribbon should at least correspond with the width of the liner material.

# DE KONINGH

 $\blacksquare$  standard  $\Box$  option

## Technical data

Setup options		
	Print	Region:
	Labels	
		- Language
	Ribbon	- Country
	Tear-off	- Keyboard
	Cut	- Time zone
	Interfaces	Time
	Error	Display:
		- Brightness
		- Power saving mode
		- Orientation
		Interpreter
Status bar	Data sasatias	Diverse
	Data reception Record data stream	Bluetooth WLAN
	Ribbon pre-warning	Ethernet
	SD memory card plugged	USB slave
	USB memory stick plugged	Time
Monitoring	D'h h	D. d. L
	Ribbon pre-warning	Periphery error
	End of ribbon	Print head voltage
	End of material	Print head temperature
		Print head open
Test routines		
System diagnostics	on start-up, including print h	
Information display,	Status printout	Test grid
test printout,	Fonts list	Label profile
analysis	List of devices	List of events
	WLAN status	Monitor mode
Status reports	- Printout of device settings,	
·	e.g. print lengths and servi	ce hours
	- Device status request by so	
	- Display of, e.g., network en	
	barcode errors, periphery	
Fonts		,
Font types	5 bitmap fonts:	7 vector fonts:
internally provided	12 x 12 dots	AR Heiti Medium GB-Mono
	16 x 16 dots	CG Triumvirate Condensed Bold
	16 x 32 dots	Garuda
	OCR-A	HanWangHeiLight
	OCR-B	Monospace 821
		Swiss 721
		Swiss 721 Bold
to be stored	TrueType fonts	
Character sets	Windows-1250 to -1257	057 062 064 066 060
Character sets	DOS 437, 737, 775, 850, 852,	857, 862, 864, 866, 869
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500	
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to	
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500	
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to	
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8	
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman	
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS	
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R	-16
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European	-16 Cyrillic
Character sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European	-16 Cyrillic Greek
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified	-16 Cyrillic Greek Latin
Cnaracter sets	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional	Cyrillic Greek Latin Hebrew
	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional Thai	Cyrillic Greek Latin Hebrew Arabic
Character sets  Bitmap fonts	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional Thai	Cyrillic Greek Latin Hebrew Arabic
	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional Thai Widths and heights 1 - 3 mm Zoom factors 2 to 10	Cyrillic Greek Latin Hebrew Arabic
Bitmap fonts	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional Thai Widths and heights 1 - 3 mm Zoom factors 2 to 10 Orientations 0°, 90°, 180°, 27	Cyrillic Greek Latin Hebrew Arabic
	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional Thai Widths and heights 1 - 3 mm Zoom factors 2 to 10 Orientations 0°, 90°, 180°, 27 Size in width and height 0,9	Cyrillic Greek Latin Hebrew Arabic
Bitmap fonts	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional Thai Widths and heights 1 - 3 mm Zoom factors 2 to 10 Orientations 0°, 90°, 180°, 27 Size in width and height 0,9 Variable zoom	Cyrillic Greek Latin Hebrew Arabic
Bitmap fonts Vector / TrueType fonts	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional Thai Widths and heights 1 - 3 mm Zoom factors 2 to 10 Orientations 0°, 90°, 180°, 27 Size in width and height 0,9 Variable zoom Orientation 360° in steps of 1	Cyrillic Greek Latin Hebrew Arabic  10° - 128 mm
Bitmap fonts	DOS 437, 737, 775, 850, 852, EBCDIC 500 ISO 8859-1 to -10 and -13 to WinOEM 720 UTF-8 MacRoman DEC MCS KOI8-R Western European Eastern European Chinese simplified Chinese traditional Thai Widths and heights 1 - 3 mm Zoom factors 2 to 10 Orientations 0°, 90°, 180°, 27 Size in width and height 0,9 Variable zoom	Cyrillic Greek Latin Hebrew Arabic  0° - 128 mm 1° ine, inverse

Graphics					
Graphic elements	·	Lines, arrows, rectangles, circles, ellipses - filled or filled with fading			
Graphic formats		PCX, IMG, BMP, TIF, MAC, GIF, PNG			
Barcodes					
Linear		Code 39, Code 93 Code 39 Full ASCII Code 128 A, B, C EAN 8, 13 EAN/UCC 128/GS1-128 EAN/UPC Appendix 2 EAN/UPC Appendix 5 FIM HIBC	Interleaved 2/5 Ident and routing code of Deutsche Post Codabar JAN 8, 13 MSI Plessey Postnet RSS 14 UPC A, E, E0	•	
2D and stacked		DataMatrix DataMatrix Rectangle Extension QR code Micro QR code GS1 QR code GS1 DataMatrix PDF 417 Micro PDF 417 UPS MaxiCode GS1 DataBar Aztec Codablock F RSS 14 truncated, limited, stacked, stacked omni-directional All codes are variable in terms of height, modular width and ratio; orientations 0°, 90°, 180°, 270° check digit, plain text printout and start / stop code are options depending from the type of code			
Software					
Label software		cablabel S3 Lite cablabel S3 Viewer cablabel S3 Pro cablabel S3 Print			
Also running	with	CODESOFT NiceLabel BarTender			
Stand-alone oper	ation				
Windows printer drivers WHQL certified	for	Windows Vista Windows 7 Windows 8 Windows 8.1 Windows 10	Server 2008 Server 2008 R2 Server 2012 Server 2012 R2 Server 2016 Server 2019		
Apple Mac OS X printer drivers		from version 10.6			
Linux printer drivers		from CUPS 1.2		•	
Programming		JScript printer language abc Basic Compiler			
Integration		SAP Database Connector			
Administration		Printer control Configuration in Intranet Network Manager (in pre			

cab uses free and Open Source Software in its products. For information see **www.cab.de/opensource** 



# DE KONINGH

Geograaf 8 | 6921 EW Duiven | T: +31 (0)26 741 00 00 | info@dekoningh.nl | www.dekoningh.nl

